

3UA Series Thermal Relay



3UA-80/Z



3UA-135



3UA-150



3UA-180/F



3UA-400/F
3UA-630/F

Type	Number	Setting range (A)	For contactor	Type	Number	Setting range (A)	For contactor		
3UA-32/Z	1G	4~6.3	CJX1-32	3UA-63/F	0K	0.8~1.25	CJX1-09~63		
	1J	6.3~10			1A	1~1.6			
	2A	10~16			1B	1.25~2			
	2B	12.5~20			1C	1.6~2.5			
	2C	16~25			1D	2~3.2			
	2D	20~32			1E	2.5~4			
	2Q	25~36			1F	3.2~5			
3UA-45/Z	0A	0.1~0.16	CJX1-32 CJX1-38		1G	4~6.3		CJX1-85 CJX1-110	
	0C	0.16~0.25			1H	5~8			
	0E	0.25~0.4			1J	6.3~10			
	0G	0.4~0.63			1K	8~12.5			
	0J	0.63~1			2A	10~16			
	0K	0.8~1.25			2B	12.5~20			
	1A	1~1.6			2C	16~25			
	1B	1.25~2		2D	20~32				
	1C	1.6~2.5		2E	25~40				
	1D	2~3.2		2M	32~45				
	1E	2.5~4		2T	40~57				
	1F	3.2~5		2P	50~63				
	1G	4~6.3		2H	55~80				
	1H	5~8		2W	63~90				
3UA-80/Z	1J	6.3~10	CJX1-45 CJX1-63 CJX1-75 CJX1-85	3UA-135	2X	80~110	CJX1-140		
	2A	10~16			3H	90~120			
	2B	12.5~20			3J	110~135			
	2C	16~25			2H	55~80			
	2D	20~32			2W	63~90			
	2Q	25~36			2X	80~110			
	2R	32~40		3H	90~120	CJX1-200			
	8M	36~45		3J	110~135				
	1G	4~6.3		3K	120~150				
	8A	11~17		3L	135~160				
	2B	12.5~20		3M	150~180				
	2C	16~25		2K	80~125				
	3UA-80/Z	2D		20~32	CJX1-09~63	3UA-180/F	2W	63~90	CJX1-110~400
		2E		25~40			2X	80~110	
2F		32~50	3H	90~120					
2T		40~57	3J	110~135					
2P		50~63	3K	120~150					
2V		57~70	3L	135~160					
2U		63~80	3M	150~180		CJX1-400			
8W		70~88	2K	80~125					
0A		0.1~0.16	3B	125~200					
0C		0.16~0.25	3C	160~250					
0E		0.25~0.4	3D	200~320					
0G		0.4~0.63	3E	250~400					
3UA-63/F		0J	0.63~1	CJX1-09~63		3UA-400	3F	320~500	CJX1-400
		0K	0.8~1.25				3G	400~630	
	0L	1~1.6							
	0M	1.25~2							