




XB2 & XD2 Pilot Light & Pushbutton



XB2-BW8465



XB2-BV64



XB2-BV74



XB2-BW3361



XB2-BK2365



XD2-PA11
XD2-PA12



XD2-PA22
XD2-PA24

Description	Contact type	Scheme	Degree of protection	Reference
Without pilot light 1 flush green pushbutton 2 pilot with Yellow lens Direct supply 380V BA 9s bulb not included 1 projecting red pushbutton	N/O	Unmarked	IP40	XB2-BW8365
	+	I O	IP40	XB2-BW8465
	NC			
1 flush green pushbutton 2 pilot with Yellow lens 220/250V supply direct through resistor BA 9s, 130V bulb included 1 protecting red pushbutton	N/O	Unmarked	IP40	XB2-BW8375
	+		IP40	XB2-BW8475
	NC	I O		
1 flush green pushbutton 2 pilot with Yellow lens 1.2VA-220V 50Hz supply via integral transformer BA 9s, 130V bulb included 1 protecting red pushbutton	N/O	Unmarked	IP40	XB2-BW8345
	+		IP40	XB2-BW8445
	NC	I O		

Supply	Supply voltage	Color	Reference
Direct Bulb not supplied	<380V 50Hz	Green	XB2-BV63
		Red	XB2-BV64
		Yellow	XB2-BV65
Direct through resistor BA9s, 6V, bulb supplied	220V-240V 50Hz	Green	XB2-BV73
		Red	XB2-BV74
		Yellow	XB2-BV75
Via integral transformer BA9s, 6V, bulb supplied	110V 50Hz	Green	XB2-BV33
		Red	XB2-BV34
		Yellow	XB2-BV35
	220V-240V 50Hz	Green	XB2-BV43
		Red	XB2-BV44
		Yellow	XB2-BV45
	380-415V 50Hz	Green	XB2-BV53
		Red	XB2-BV54
		Yellow	XB2-BV55
Illuminated flush pushbuttons with N/O contact			
Direct Bulb not supplied	<380V 50Hz	Green	XB2-BW3361
		Red	XB2-BW3461
		Yellow	XB2-BW3561
Direct through resistor BA9s, 6V, bulb supplied	220V-240V 50Hz	Green	XB2-BW3371
		Red	XB2-BW3471
		Yellow	XB2-BW3571

Description	Contact Type	Reference
2 Position stay put	N/C+N/O	XB2-BK2365
		XB2-BK2465
		XB2-BK2565
		XB2-BK2665
		XB2-BK2765
	N/C+N/O	XB2-BK3365
		XB2-BK3465
		XB2-BK3565
		XB2-BK3665
		XB2-BK3765
	N/C+N/O	XB2-BK5365
		XB2-BK5465
		XB2-BK5565
		XB2-BK5665
		XB2-BK5765

operation pole(operation shaft 54mm length)			
explain	contact top	the spring turn back nil position type	
operate pole(screw clamp terminal)	1N/O	without	XD2-PA11
2 direction	contact point direction	with	XD2-PA12
4 direction	1N/O contact point direction	without	XD2-PA22
		with	XD2-PA24